



Domingo French 831 - Villa Martelli - (B1603BNI) - Buenos Aires – Argentina

HOJA DE DATOS

POWER INSERT

Parameter					
Item		Specifications			
Frequency Range	MHz	5-30	30-230	230-550	550-1000
Insertion Loss	dB	0.5	0.5	0.8	1.4
Depth of RF-AC Isolation	dB	63	63-60	60-55	50
Return Loss	dB	≥ 18	≥ 16	≥ 16	≥ 16
AC Current Crossing	A	Maximum 15A (65V)			
Signal Hum Ratio	dB	≥ 66			